



BEAMZ
MADE
EAZY

151.381 V1.4

BTF300Z

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
DMX ADDR	d001-d512	DMX address setting	
MODE	DMX	1 / 2 / 3 / 4 Ch	DMX channel mode
	Auto	Program	001-005
		Speed	001-009
		Brightness	000-255
	Manual	Strobe	000-255
		Zoom	000-255
DIMMER	Curve	0.3-3.0	Dimmer curves adjustment
	Mode	Standard	Select dimmer curve
		Stage	
		TV	
		Architecture	
		Theatre	
		Studio	Studio Power mode - Silent
		Custom	
ADVANCE	Authorization	On / Off	Advanced settings for Beamz support only.
	Signal hold	On / Off	Run if signal cut
	RDM	On / Off	RDM function on / off
	Screen Timeout	30sec.	Display shut off time
		Never	
	Screen brightness	25-100%	Display brightness
	Dimming Freq	1.2-24.0 KHz	Dimmer frequency setting
	Software version	Vx.xx	Software version
RESET	Yes / No	System reset	
REVERSE	Yes / No	Display reverse 180°	

DMX CHANNELS

1 CHANNEL

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	0-100% Dimmer

2 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	0-100% Dimmer
2	ZOOM	000-255	Zoom from wide to narrow

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	0-100% Dimmer
2	STROBE	000-013	No function
		014-255	Strobe from slow to fast
3	ZOOM	000-255	Zoom from wide to narrow

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	0-100% Dimmer
2	DIMMER FINE	000-255	0-100% Dimmer fine
3	STROBE	000-013	No function
		014-255	Strobe from slow to fast
4	ZOOM	000-255	Zoom from wide to narrow



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM