

VP-2L

1:1 Computer Graphics Video Line Amplifier



Compatible with HDTV component video signals when used with a breakout cable such as the Kramer C-GM/3RVF.



The VP-2L is a high-performance line amplifier for computer graphics video signals with resolutions up to and exceeding UXGA. It provides controls to compensate for signal losses inherent in long cable runs.

FEATURES

- Resolution up to UXGA.
- HDTV Compatible.
- Level (Gain) and EQ (Peaking) Controls Recessed control trimmers to prevent tampering.
- ID Bit Control.
- Compact Size Part of the Kramer TOOLS™ family of compact, high quality and cost effective solutions.

TECHNICAL SPECIFICATIONS

INPUT:	1 UXGA on a 15-pin HD (F) connector.
OUTPUT:	1 UXGA on a 15-pin HD (F) connector.
MAX. OUTPUT LEVEL:	1.5Vpp.
RESOLUTION:	Up to UXGA.
DIFF. GAIN:	2.7%.
DIFF. PHASE:	0.09Deg.
K-FACTOR:	0.1%.
S/N RATIO:	73dB.
CONTROLS:	Level: -7.4dB to +4dB; EQ.: 0 to +26.4dB.
COUPLING:	DC.
POWER CONSUMPTION:	5V DC, 307mA.
DIMENSIONS:	4.27cm x 5.64cm x 2.2cm (1.68" x 2.22" x 0.87") W, D, H.
WEIGHT:	0.14kg (0.31lbs) approx.
INCLUDED ACCESSORIES: Power supply.	

